

Dynamic Engineers Inc.

Website: www.DynamicEngineers.com Email: lnquiry@DynamicEngineers.com

SF3030AO-1615.68MHz-A

1615.68MHz Small Size SMD SAW Filter

Features and Benefits


Center frequency: 1615.68MHz

I.L: 4dB Max.

Operating temperature: -55°C to +125°C

Size: 3x3x1.4mm

Package type: Surface Mount




Typical Applications


IOT
Cellular
Telecom
4G/LTE
Wireless Communication
WLAN
Base Station
Radar

Mechanical Drawing & Pin Connections

Drawing No:

MD240080-1





| PIN | Function | | | |
|--------|----------|--|--|--|
| #2 | INPUT | | | |
| #5 | OUTPUT | | | |
| Others | GND | | | |

Unit in mm

1mm = 0.0394 inches

Not Specified Tolerance: ±0.2mm



Dynamic Engineers Inc.

Website: www.DynamicEngineers.com Email: Inquiry@DynamicEngineers.com

SF3030AO-1615.68MHz-A 1615.68MHz Small Size SMD SAW Filter

Specifications

| Parameter | Min. | Typical | Max. | Units | | |
|---|------|---------|------|-------|--|--|
| Center Frequency Fc | | 1615.68 | | MHz | | |
| Insertion Loss (1611.6~1619.76 MHz) IL | | 2.2 | 4 | dB | | |
| Amplitude Ripple (1611.6~1619.76 MHz) | | 0.6 | 2 | dB | | |
| Bandwidth @ -3dB | 8.16 | 29 | | MHz | | |
| Attenuation (Reference level from 0 dB) | | | | | | |
| 1515.68~1570 MHz | 38 | 45 | | dB | | |
| 1580 MHz | 30 | 51 | | dB | | |
| 1650 MHz | 30 | 53 | | dB | | |
| 1660~1715.68 MHz | 50 | 59 | | dB | | |
| Temperature Coefficient of Frequency | | -36 | | ppm/k | | |
| Input Power Level | | 13 | | dBm | | |
| DC Voltage | | 3 | | V | | |
| Operating Temperature Range | -55 | | +125 | °C | | |
| Storage Temperature Range | -55 | | +125 | °C | | |